

10 Way Stereo Audio/ Video Distribution Amplifier


Operation Manual

Features

1. Lets you make up to 10 loss free video copies or display the output of one VCR on up to 10 TVs.
2. Loop through facility allows you to connect further 10 way amplifiers.
3. Easy to connect- just use any Scart to Scart cables.
4. Ideal for duplication of video tapes or shop and showroom displays.

Operation Controls and Functions

Front Panel



1. Power ON/OFF switch.
Push the button to turn ON/OFF the power.
2. Power LED.


Rear Panel



1. DC 15V Input.

Operation Controls and Functions

Upper Panel



1. Input scart connector: 21-pin scart connector for Audio/Video input.
2. Output scart connectors: 21-pin scart connectors for distributed parallel Audio/ Video output.
3. Monitor or output scart connector.
4. Loop out or output scart connector: Loop to next SC-AMP1.

Scart Lead (Back of Plug View)

1. Audio output 1, right channel
2. Audio input 1, right channel
3. Audio output 2, left channel
4. GND (Audio)
6. Audio input 2, left channel
15. Chroma input 2, left channel
17. GND (Video)
19. Video or Y output
20. Video or Y input
21. Shield



P.S. All other pins are not connected.

Specifications

RGB IN/OUT: 0.7V 75 ohm

Video IN/OUT: 1 Vp-p 75 ohm

Y/C input with pin 15 and pin 20: 1 Vp-p 75 ohm

Y/C output with pin 15 and pin 19: 1 Vp-p 75 ohm

Audio IN/OUT: Through out

Video frequency: > 10 MHz(-3dB)

Differential gain: <2%

Differential phase: <2 Deg

Power: Output: 15 Volt/500 mA AC adaptor